

Offener Kleintransformator für gedruckte Schaltungen

Baugröße	Leistung VA	Maße in ca. mm									Gewicht			
		a	b	c	d	e	f	Rastermaße	h	i	Wirkungsgrad %	Spannungsabfall %	Cu-Gewicht ca. kg	Gesamtgewicht ca. kg
EI 30/ 12.5	1,2	30,0	25,0	26,5	-	-	-	4x5	20,0	6,2	45,0	36,0	0,010	0,070
EI 30/ 15.5	1,8	30,0	25,0	29,0	-	-	-	4x5	20,0	6,2	40,0	40,0	0,015	0,100
EI 38/ 13.6	3,2	38,0	32,0	30,5	-	-	-	4x5	25,0	6,2	58,0	32,0	0,025	0,160
EI 38/ 16.3	3,8	38,0	32,0	33,1	-	-	-	4x5	25,0	6,2	60,0	35,0	0,030	0,170
EI 42/ 14.8	4,5	42,0	35,0	31,0	35,0	28,5	3,5	5/7,5/7,5/5	25,0	6,2	66,0	22,0	0,030	0,170
EI 48/ 16.8	8,0	48,0	40,0	36,0	40,0	32,0	4,0	5x5	27,5	6,2	70,0	20,0	0,050	0,240
EI 48/ 20.5	10,0	48,0	40,0	38,7	40,0	32,0	4,0	5x5	27,5	6,2	71,0	20,0	0,060	0,260
EI 54/ 18.8	16,0	54,0	45,0	40,0	45,0	36,0	4,5	7,5/10/10/7,5	30,0	6,2	71,0	22,0	0,080	0,350
EI 60/ 21.0	20,0	60,0	50,0	45,0	50,0	40,0	5,0	6x5	32,5	6,2	75,0	17,0	0,110	0,500
EI 66/ 23.0	30,0	66,0	55,0	47,0	55,0	44,0	5,5	7x5	35,0	6,2	78,0	17,0	0,140	0,700
EI 66/ 30.0	40,0	66,0	55,0	54,0	55,0	44,0	5,5	7x5	35,0	6,2	78,0	14,0	0,170	1,000
EI 66/ 34.8	50,0	66,0	55,0	58,0	55,0	44,0	5,5	7x5	35,0	6,2	80,0	11,0	0,190	1,200
EI 78/ 27.5	63,0	78,0	65,0	55,0	65,0	52,0	6,5	8x5	42,5	6,2	80,0	12,0	0,250	1,100
EI 78/ 36.5	75,0	78,0	65,0	65,0	65,0	52,0	6,5	8x5	42,5	6,2	82,0	11,0	0,270	1,400
EI 78/ 40.5	85,0	78,0	65,0	69,0	65,0	52,0	6,5	8x5	42,5	6,2	83,0	11,0	0,290	1,550
EI 84/ 43.5	110,0	84,0	70,0	74,0	70,0	56,0	7,0	9x5	45,0	6,2	84,0	9,0	0,350	2,000